ELECTRONIC PRODUCT FORM

4/02/04	DMKI-FPTE1810313R0
---------	--------------------

designation	HEADBOX RECEIVER RTS (RTS PLATEN CABLE 3M)	
reference	1810314	
range		

DESCRIPTION

The **PLATINE RTS SOMFY** is a radio receiver for LT motors that can be installed inside the pelmet of the roller shutter.

The **PLATINE RTS SOMFY** is compatible with the following RTS controls and sensor (up to 12 controls and 3 sensors can be memorized):

CENTRALIS RTS TELIS 1 RTS INIS RT TELIS 4 RTS CHRONIS RTS TELIS soliris RTS

SOLIRIS sensor RTS (SUN ONLY) **TELIS soliris lighting RTS**



R&TTE 1999/5/CE

With the **PLATINE RTS SOMFY** and a RTS control, it is possible to set one or two intermediate positions (IP): one accessible from the top of the roller shutter and one from the bottom.

The **PLATINE RTS SOMFY** is compatible with the Easy Manufacturing Setting (EMS)

TECHNICAL SPECIFICATIONS			
Вох	Material Color Size weight	PVC with resin black 120 x 45 x 24 mm 0,285 Kg	
Power supply		230Vac 50Hz 3A	
Output load		max. 3A 250VAC cosf0,9	
Protection index		IP44	
Temperature range	Working Storage	-30°C to +80°C -30°C to +70°C	
Cables	power supply motor	VVF 3m 3 wires VVF 0,20m LT plug	
Frequency Antenna	diameter lenght	433,42Mhz 3mm 180mm	
Standards		EN 60730-2-1 EN 301489-3 ETS 300 220-3	

